



Three phase Wiring Key

<p><u>Wire Number + Color</u></p> <p>1 = Blue 2 = White 3 = Orange 4 = Yellow 5 = Black 6 = Violet 7 = Pink 8 = Red 9 = Gray 10 = Black 11 = Black 12 = Black Green = Ground</p>	<p><b><u>220V, Low Voltage</u></b> Cap the Following Wires as pairs. 10+4, 11+5, 12+6</p> <p>The Following are connected to the incoming lines.</p> <p><b><u>Line 1</u></b> 1+7</p> <p><b><u>Line 2</u></b> 2+8</p> <p><b><u>Line 3</u></b> 3+9</p>
	<p><b><u>440V, High Voltage</u></b> Cap the following lines all together. 10+11+12</p> <p>Cap The Following Wires as Pairs 4+7, 5+8, 6+9</p> <p>The Following are connected to the incoming lines.</p> <p><b><u>Line 1</u></b> 1</p> <p><b><u>Line 2</u></b> 2</p> <p><b><u>Line 3</u></b> 3</p>

